

TYPE I—CYCLING CIRCUIT BREAKERS (cont)

No. 30401

- Dimples stamped in case provide secure anchorage for snap-in brackets.
- Two blade terminals 1.08" (26.70mm) in center.
- Overall size (L x W x H): 1 1/4" x 25/32" x 1 3/64" (31.8mm x 19.81mm x 26.7mm).



Amperes	CH Part No.
4	30401-4
6	30401-6
8	30401-8
10	30401-10
15	30401-15

No. 30404

- Double blade terminal on one end and a #10-32 stud terminal on the other.
- Dimples stamped in case to provide secure anchorage.
- Overall size (L x W x H): 1 1/4" x 25/32" x 1 13/64" (31.8mm x 19.81mm x 30.48mm).



Amperes	CH Part No.
20	30404-20
30	30404-30

No. 30063

- Environmentally sealed for exposed applications.
- Wire leads are heavy gauge SAE type wire, color coded for easy identification.
- Easy to install - cut wire loop at desired point and splice into circuit.
- Overall size (L x W x H): 2" x 7/8" x 1" (50.8mm x 22.22mm x 25.4mm).




Amperes	CH Part No.	Wire Gauge	Code
20	30063-20	14	Black
30	30063-30	12	Red
40	30063-40	12	Brown

DOUBLE BREAKER ASSEMBLIES FOR HIGHER RATINGS

No. 3088

- "Length-wise" bracket.
- #10-32 stud terminals with hex nuts and lock washers.
- Overall size (L x W x H): 2" x 1 5/8" x 1 25/64" (50.8mm x 41.4mm x 35.2mm).



No. 30507


Amperes	CH Part No.	Sealed
50	3088-50	No
50	30507-50	Yes
60	3088-60	No
60	30507-60	Yes
80	3088-80	No
80	30507-80	Yes

TYPE II—NON-CYCLING CIRCUIT BREAKERS

GLASS FUSE CLIP MOUNTING

No. 30410

- For 12V (dc) systems only.
- Replaces 3AG (AGC) and SFE 20 amp glass fuses.
- Snap in mounting in standard fuse clips.
- Size: (W x H): 1 1/4" x 43/64" (31.7mm x 17.9mm).



Amperes	CH Part No.	Replaces Ford No.
10	30410-10	DOHB-14526-A
15	30410-15	DOVB-14526-A
20	30410-20	DOVB-14526-B
25	30410-25	DOHB-14526-B
30	30410-30	DOVB-14526-C

PLUG-IN TYPE

No. 30403

- Designed to fit Mack Truck breaker blocks.
- Male blade terminals on 1.00" (25.4mm) centers.



Amperes	CH Part No.
15	30403-15
20	30403-20
25	30403-25
30	30403-30

No. 30408

- Designed to fit Navistar (IHC) breaker blocks.
- Male blade terminals on 1.08" (27.4mm) centers.




Amperes	CH Part No.
10	30408-10
15	30408-15
20	30408-20
30	30408-30
35	30408-35

MECHANICAL RE-SET TYPE

No. 30407

Molded Plastic Housing

- Remains open on overload until re-set button is depressed.
- "Cross-wise" bracket.
- Two #10-32 stud terminals with hex nuts and lock washers provided.



Amperes	CH Part No.
15	30407-15
20	30407-20
25	30407-25
30	30407-30
40	30407-40
50	30407-50

MOUNTING BRACKETS

No. 30090

- Accommodates all SAE type breakers without brackets including CH Series Nos. 30056, 30137, 30401, 30144, 30404.
- Circuit breakers snap in.
- Hold breakers securely.
- Heavy gauge steel.



Gangs	CH Part No.	Dimensions (L x W)
2	30090-2	4.81" x 1.29" (122.17mm x 32.76mm)
3	30090-3	5.71" x 1.29" (145.03mm x 32.76mm)
4	30090-4	6.62" x 1.29" (160.14mm x 32.76mm)
6	30090-6	8.43" x 1.29" (214.12mm x 32.76mm)
8	30090-8	10.25" x 1.29" (260.35mm x 32.76mm)



Lake-View Electronics Corp.
Phone: 1-800-686-8439
Fax: 262-375-0109